

## RECORDING AND SENDING MESSAGES

### Sending voice or voice-fax messages

1. From the activity menu [1]
2. Record voice message
3. When finished [#]
4. Specify delivery address (see below)
5. When finished [#]
6. Specify delivery options (see below)
7. Send message [#]

### Sending fax-only messages from fax machine

1. From the activity menu [1]
2. Bypass voice recording [#]
3. Specify delivery address (see below)
4. When finished [#]
5. Specify delivery options (see below)
6. Load document into fax machine
7. Send message [#]
8. Press **Start** key on fax machine

### Sending voice-fax messages by forwarding a fax

To send a fax to your own mailbox:

1. Log in to mailbox
2. From the activity menu [2]
3. Forward fax with optional voice message [1] [2]
4. Record voice message
5. When finished [#]
6. Specify delivery address (see below)
7. When finished [#]
8. Specify delivery options (see below)
9. Send message [#]

### Specifying delivery address

- For voice user:  
Enter user's mailbox number, and press [#]
- For voice user name addressing:  
Press [\*] [2], spell user's name or name of personal list, and press [#]
- For personal list, press [\*] [5] and then list number
- For fax user:  
Press [\*] [\*] [5], enter outside line number (if needed) and telephone number, and then press [#]
- To cancel address: press [\*] [3]
- To cancel another address: press [\*] [1] [\*] [3]
- To list all recipients: press [\*] [1]

### Specifying delivery options

- Make private/not private (toggle) [1]
- Make priority/not priority (toggle) [2]
- Schedule for future delivery [3]
- Attach a fax [5]

## GETTING MESSAGES YOU RECEIVED

### Listening to voice/e-mail messages

1. From the activity menu [2]
2. Listen to voice or e-mail message [0]

### Responding to messages (optional)

After listening to your message, press [1] to respond to or forward the message. Then select one of the following:

- Call sender (exits mailbox) [0]
- Reply to sender by voice mail [1]
- Forward with comment at beginning [2]
- Record and address a new message [4]
- Reply to all recipients [5]

If you select any key from the above except [0]:

1. Record and address your message
2. When finished [#]
3. Specify delivery options
4. Send message [#]

### Printing fax/e-mail messages

1. From the activity menu [2]
2. Listen to message header
3. Print fax or e-mail portions [\*] [1]
4. Print to default machine [#]

#### OR

- To print to the fax machine from which you are calling [\*] [6]

#### OR

- To print to other fax machine you specify:
  - Press [\*] [\*] [5]
  - Enter outside line number (if needed) and telephone number
  - Press [#]

## GENERAL TIPS

### Not sure which key to press?

- Listen to Help at any time [\*] [4]
- Go back to activity menu [\*] [7]

### Want to save time?

- Bypass greeting when recording [1]
- Bypass header when listening [0]

### Want to adjust the way your messages are played?

- Faster [9]
- Slower [8]
- Louder [4]
- Softer [7]
- Skip forward [6]
- Skip backward [5]

### Want to configure Personal Operator?

- To set up or change Personal Operator [5] [6]

### Other options

- Transfer to covering extension [\*] [0]
- Transfer to another mailbox [\*] [8]
- Make system wait [\*] [9]
- Access names or numbers directory [\*] [\*] [6]
- Disconnect [\*] [\*] [9]

## CREATING MULTIPLE PERSONAL GREETINGS

### Creating, changing, deleting greetings

1. From the activity menu [3]
2. Do one of the following:
  - Listen to a greeting [0]
  - Record or re-record a greeting [1]
  - Delete a greeting [3]
3. Enter greeting number [1-3]
4. For optional greetings only, enter the optional greeting number [1-9]
5. If Multilingual Call Answer is enabled, a language select [1-3]
6. When finished [#]

### Scanning greetings

1. From the activity menu [3]
2. Scan greetings [2]

### Activating greetings

1. From the activity menu [3]
2. Activate greeting [5]
3. Enter greeting number [1-3]
4. For personal greeting only, you may need to confirm your choice [1]
5. For optional greetings only, enter the optional greeting number [1-9]

### Setting up rules for optional greetings

- Activate for all calls [0]
- Activate for internal calls → external calls → all calls (rotate) [1]
- Activate for business hours → out of business hours → any time (rotate) [2]
- Activate for busy → no answer → busy or no answer (rotate) [3]
- Deactivate for all calls [9]

### Reviewing optional greeting rules

1. From the activity menu [3]
2. Review optional greeting rules (in the order they will be evaluated) [6]

### Setting up Call Me/Find Me/Notify Me options

1. From the activity menu [6]
2. Select one of the following:
  - Call Me [1]
  - Find Me [2]
  - Notify Me [3]
3. Select one of the following:
  - Enable Call Me/Find Me [9]
  - Disable Call Me/Find Me [6]

**NOTE:** *Your system may not support all features.*

Copyright © 2006-2007, Avaya, Inc. All rights reserved. All trademarks identified by ® and ™ are registered trademarks or trademarks respectively of Avaya Inc. All other trademarks are the properties of their respective owners.

**Disclaimer:** Avaya is not responsible for any modifications, additions or deletions to the original published version of this documentation unless such modifications, additions or deletions were performed by Avaya. Customer and/or end user agree to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation to the extent made by the customer or end user.



**AUDIX® Telephone  
User Interface for  
Avaya™ Modular Messaging**

**QUICK REFERENCE GUIDE**

## ABOUT THIS GUIDE

This quick reference guide provides step-by-step instructions on how to perform important tasks when using the Modular Messaging system through the AUDIX® telephone user interface (TUI). For additional information, consult the Modular Messaging TUI guide.

**Note:** Depending on the way your system is set up, some features in this guide may not be available.

## Accessing your mailbox

### From your office extension:

1. Call the system access number.
2. Enter your password followed by [#].

### From someone else's office extension or from outside of your office:

1. Call the system access number.
2. Do one of the following:
  - If you are prompted to enter the password for the extension from which you are calling, press [\*] [#].
  - If you are prompted to enter the extension of the person you are calling, press [#].
3. Enter your mailbox number.
4. Enter your password followed by [#].

